



说明NOTE:

- 1.红色引线: 供电电源端, 24.0VDC. (电压范围: 20-25.0VDC).
- 2.黑色引线为电源负极.
- 3.白色引线为正反反转控制端. 当此脚悬空时, 电机转向为CCW, 当此脚与电源负极连接时, 电机转向为CW.
- 4.电源正负极切勿接错, 否则会损坏机器. 正反反转控制端切勿与正极发生碰触, 否则会损坏机器.

MOTOR TORQUE/SPEED/CURRENT

RATED VOLTAGE	24.0VDC
NO LOAD SPEED	4500RPM
NO LOAD CURRENT	0.10A
RATED TORQUE	200g.cm
RATED CURRENT	0.5A
RATED SPEED	3450RPM

				MATL.	<input type="checkbox"/> CRITICAL DIM. <input type="checkbox"/> CONTROL DIM.			
				SCALE: 1:1	PART NO. HC3650BS-24V-0.10A-4500			
		X	±0.3	<PROJ:	TITLE. MOTOR OUTLINE 马达外型图			
		X.X	±0.1	SUNNY 深圳宏业欣电子有限公司 HONGYEXIN ELECTRON CO.,LTD	DWN.BY	CHKD. BY	APPD. BY	FINAL. SPPD
		X.XX	±0.05				张天波	
REV.	WAS.	ANGULAR	±5°					